

Go Series G440

4K 8MP 4G LTE Wireless Battery/Solar Powered PT Outdoor Camera with Smart Detection & Color Night Vision

- 4K 8MP Ultra HD
- 4G LTE Network
- Color Night Vision

Specifications

| Video & Audio | |
|--------------------------|---|
| Image Sensor | 1/2.7" CMOS Sensor |
| Video Resolution | 3840 x 2160 (8 Megapixel)@15fps |
| Video Compression | H.265 |
| Field of View | Fixed Lens, Horizontal: 90°, Vertical: 47° , Diagonal: 110° |
| Infrared Night Vision | Up to 10 Meters (33ft) (LED: 2pcs/1.2W/850nm) |
| Color Night Vision | Spotlight: 2pcs/2.4W/6500K |
| Audio | Two-Way Audio |
| Alarm | |
| Smart Alarm | PIR/person/vehicle/animal detection |
| PIR Detecting Distance | Adjustable up to 10m (33 ft) |
| PIR Detecting Angle | 120° Horizontal |
| Audio Alert | Customized Audio Alerts |
| Recording | Motion-Triggered Recording |

| | |
|----------------------------|--|
| Other Alerts | Instant Email Alerts and Push Notifications |
| Pan & Tilt | |
| Pan &Tilt | 355° Pan, 140° Tilt |
| Preset Points | Supports 1 guard position & up to 32 preset positions |
| 3G/4G Bandwidth | |
| Frequency Bands | <ul style="list-style-type: none"> • Europe Version: LTE FDD: B1/B3/B7/B8/B20/B28A WCDMA: B1/B8 • USA Version: LTE FDD: B2/B4/B5/B12/B13/B14/B66/B71 • Australia Version: LTE FDD: B1/B3/B5/B7/B8/B28 WCDMA: B1/B5/B8 |
| Power | |
| Battery | 21.6Wh Rechargeable Battery (Battery life varies based on settings, usage & temperature) |
| Solar | Reolink Solar Panel 2 |
| DC Power | USB Type-C port |
| Storage | |
| Local Storage | microSD Card (32GB included, max. 128GB) |
| Cloud Storage | Reolink Cloud (only available in some countries) |
| Smart Home | |
| Smart Home | Google Assistant |
| Working Environment | |
| Operating Temperature | -10 to 55° C (14° to 131° F) |
| Weather Resistance | IP64 |
| Size & Weight | |
| Size | Φ98 x 122mm |

| | |
|---------------------------|---|
| Weight (Battery included) | 496g |
| Warranty | |
| Limited Warranty | 2-year limited warranty. For support, visit https://support.reolink.com/hc/en-us/ |

Gallery & Specs



1. Speaker
2. IR LEDs
3. Spotlights
4. Daylight Sensor
5. Lens
6. Status LED
7. PIR Motion Sensor
8. Built-in Microphone



1. IR LEDs
2. Status LED
3. Daylight Sensor
4. Lens
5. Built-in Mic
6. PIR Motion Sensor
7. USB-C Port
8. Speaker